

EVAL-FE50MSIR



DC-50 MBd SMI Evaluation Kit User Guide

OVERVIEW

Eval-FE50MSIR evaluation kit enables evaluation of the Firecomms DC-50 MBd inverting (Rx) SMI transceiver for Plastic Optic Fiber (POF) and large core glass fiber (200, 400 um PCS). The kit includes a single SMI transceiver pre-mounted onto a simple PCB that allows easy application of DC power via standard 2 mm diameter DC jacks. Data input (TXD) and data output (RXD) are connected via standard screw terminal SMA connectors. An SMI long body plug with 1m of simplex POF cable in a loop back is also included. For particular lengths of POF or PCS fibers and assemblies please contact Firecomms Applications support directly.





FIGURE 1
Recommended circuit layout for the DC-50 MBd SMI transceiver

EVALUATION KIT CONTENTS

The Evaluation Kit contains the following:

1. Evaluation PCB
2. FE50MSIR mounted onto the evaluation PCB
3. Long body SMI plug FP-00C-3F0 with loop-back POF cable (1 m, 0.5 NA, 2.2 mm jacket simplex POF)
4. FE50MSIR Datasheet

DC-50 MBd SMI Evaluation Kit User Guide

INITIAL SETUP

1. Connect GND of a DC power supply to the ground points of the PCB (black terminals).
2. Connect 3.3 / 5 V to each of the Tx and Rx VCC jacks (red terminals).
3. To measure common GND, connect a probe to the test points TP1 (Tx) and TP2 (Rx).
4. Connect suitable pattern generator signal via an SMA cable to the TXD data pin.
5. Connect the RXD data pin (TTL output) to a suitable high-speed oscilloscope using 1 M Ω termination and high-speed coax, SMA terminated cable.
6. For a loop-back cable test, insert the SMI long body plug with 1m of looped back simplex POF cable into the SMI transceiver.




FIGURE 2
Setup of the FE50MSIR Evaluation PCB

For the most recent revision or further information please visit www.firecomms.com or contact the company directly at the following address, Firecomms Ltd, 2200 Airport Business Park, Cork, IRELAND. Copyright© 2004-2023 Firecomms. All rights reserved. Firecomms refers to Firecomms Limited and/or its subsidiaries. Firecomms assumes no responsibility for inaccuracies or omissions in the information contained in this document. Specifications are subject to change without notice. No patent rights are granted to any of the circuits described herein.